

デジタイザーMBX V5 インストール途中で『Security Error』のメッセージが表示され、インストールが完了しない場合があります。



この問題は、Sentinel HASP ドライバをアップデートすることで解決する可能性が高いため、下記の手順に従ってドライバのアップデートを行ってから再度インストールを行ってください。

はじめに

- ・ パソコンをインターネットに接続してください。
- ・ 旧デジタイザーのUSB dongle がパソコンに刺さっている場合は外してください。
- ・ セキュリティソフトは一時的に無効にしてください。

HASP ドライバのアップデート

① 下記のリンクより、THALES社のSentinel HASPドライバ最新バージョンのダウンロードページに飛んでください。

※2021年3月16日現在の最新バージョンは8.15ですが、末尾のバージョンを示す数字はアップデート状況によって変わることがあります。

https://supportportal.thalesgroup.com/csm?sys_kb_id=61fb0ee1dbd2e78cfe0aff3dbf9619ab&id=kb_article_view&sysparm_rank=8&sysparm_tsqueryId=d846bbc81b511450f12064606e4bcbf6&sysparm_article=KB0018320

HASPドライバのアップデート

②ダウンロード用のページが表示されます。『DOQ0003347』をクリックします。

Sentinel HASP/LDK Windows GUI Run-time Installer 8.11
KB0018320

Article Details KB0018320

2020-06-04 04:10:40 • ★★★★★

Sentinel® LDK and Sentinel HASP® Run-time Environment Installer GUI for Windows
Refer to the Readme file included in the package for details.

MD5 (Sentinel_LDK_Run-time_setup.zip) = ed87335be74192a3325830502e5fdc54

Click here to download file: [DOW0003347](#)

③同意書が表示されます。

End User License Agreement

SafeNet

SAFENET END USER LICENSE AGREEMENT

IMPORTANT INFORMATION - PLEASE READ THIS AGREEMENT CAREFULLY BEFORE USING THE CONTENTS OF THE PACKAGE AND/OR BEFORE DOWNLOADING OR INSTALLING THE SOFTWARE PRODUCT. ALL ORDERS FOR AND USE OF THE SENTINEL®, Hardlock, HASP®, and SmartKey PRODUCTS, (including without limitation, the Developer's Kit, libraries, utilities, CD-ROM, DVD, Protection keys, the software component of SafeNet Sentinel LDK and the Sentinel LDK Software Protection and Licensing Guide), (hereinafter "Product") SUPPLIED BY SAFENET, INC., (or any of its affiliates - either of them referred to as "SAFENET") ARE AND SHALL BE, SUBJECT TO THE TERMS AND CONDITIONS SET FORTH IN THIS AGREEMENT.

BY OPENING THE PACKAGE CONTAINING THE PRODUCTS AND/OR BY DOWNLOADING THE SOFTWARE (as defined hereunder) AND/OR BY INSTALLING THE SOFTWARE ON YOUR COMPUTER AND/OR BY USING THE PRODUCT, YOU ARE ACCEPTING THIS AGREEMENT AND AGREEING TO BE BOUND BY ITS TERMS AND CONDITIONS.

IF YOU DO NOT AGREE TO THIS AGREEMENT OR ARE NOT WILLING TO BE BOUND BY IT, DO NOT OPEN THE PACKAGE AND/OR DOWNLOAD AND/OR INSTALL THE SOFTWARE AND PROMPTLY (at least within 7 days from the date you received this package) RETURN THE PRODUCTS TO SAFENET, ERASE THE SOFTWARE, AND ANY PART THEREOF, FROM YOUR COMPUTER AND DO NOT USE IT IN ANY MANNER WHATSOEVER.

This Agreement has 3 sections:

Section I applies if you are downloading or using the Product free of charge for evaluation purposes only.

Section II applies if you have purchased or have been otherwise granted by SafeNet a license to use the Product.

Section III applies to all grants of license.

SECTION I - TERMS APPLICABLE TO GRANT OF EVALUATION LICENSE

④同意書を読み、ページ下部の ☒ I accept (同意します) をクリックします。

ISO 9001:2000 Certification

REGISTERED COMPANY
ISO 9001:2008
SafeNet

The HASP product line is designed and manufactured by SafeNet Data Security (Israel) Ltd., an ISO 9001:2008 certified company. SafeNet's quality assurance system is approved by the International Organization for Standardization (ISO), ensuring that SafeNet products and customer service standards consistently meet specifications in order to provide outstanding customer satisfaction.

Certificate of Compliance

Upon request, SafeNet will supply a Certificate of Compliance to any software developer who wishes to demonstrate that the HASP product line conforms to the specifications stated. Software developers can distribute this certificate to the end user along with their programs.

☒ I accept

HASPドライバのアップデート


④ダウンロードが開始されます。

インターネットブラウザの設定で保存先の指定ができる場合は、保存先にデスクトップなどを指定してダウンロードを行います。

保存先が分からない場合は、画面の右上のタブを開き、「ダウンロード」という項目をクリックします。




ダウンロードしたファイルの、フォルダを開くをクリックします。




HASPドライバのアップデート

⑤フォルダ内の、ダウンロードした圧縮ファイル(.zip)を **右クリック** し、表示されるメニューから解凍(パソコンによっては展開)します。

▼ 圧縮ファイルの解凍(「解凍」表記のパソコン)





右クリック



解凍先を指定しない場合、
「デスクトップに解凍(展開)」
をクリックします。


▼ 圧縮ファイルの解凍(「展開」表記のパソコン)



右クリック



※アイコンが違いますが
同じ圧縮ファイルです。




「参照」から展開先を決めることができます。
指定先に希望がない場合、
デスクトップなど分かりやすいフォルダ
にしてください。

HASPドライバのアップデート


⑥解凍(展開)したフォルダの中の、『HASP User Setup』をダブルクリックします。

名前	更新日時	種類	サイズ
Readme_HTML5	2021/03/16 12:27	ファイル フォルダー	
HASPUserSetup.exe	2021/03/16 12:26	アプリケーション	21,497 KB
Readme.html	2021/03/16 12:26	Chrome HTML Do...	1 KB

⑦「Welcome」画面が表示されますので『Next』をクリックします。




⑧ “I accept the license agreement” (使用許諾契約書に同意します) にチェックを入れ、『Next』をクリックします。



HASPドライバのアップデート

⑨もう一度『Next』をクリックすると、インストールが開始されます。



⑩『Finish』をクリックするとインストールが完了します。



⑪ 上記Sentinel HASP ドライバアップデート及びデジタイザーのインストールが完了しましたら、セキュリティソフトを有効にしてください。